

EXIDE

**POWERSAFE
PLUS**

the technology within

POWERING THE
CYBER WORLD



Winner of EFY Awards for
Best SMF Battery... 10 times in a row
2005 - 2014

Sealed Maintenance Free VRLA Batteries

Visit us at: www.exide4u.com

Presenting NEW Improved Exide Powersafe Plus, Sealed Maintenance Free VRLA batteries with enhanced design features, which give a higher performance & reliability, better suited to Indian conditions. Exide Powersafe is a product of collaborative efforts of in-house R&D of Exide Industries Ltd., the largest lead-acid battery manufacturer of India and M/s. Shin-Kobe Electric Machinery Co., Japan, the makers of world renowned Hitachi batteries. No wonder it is approved by all major OEMs and Institutional customers and is considered to be the Power Pack of the future.

HIGHLIGHTS OF THE NEW PRODUCTS: ● ABS Container & Lid ■ Better aesthetics ■ Stronger and free from distortion ● Brass Terminal with Lead Coating ■ Better conductivity ■ Free from corrosion ● Over Partition Welding ■ Free from inter-cell weld failure ● Thicker Separator ■ More acid volume ■ Better capacity retention ■ Improved electrical performance

FEATURES: | New Improved Sealed Maintenance free | Free from Orientation Constraints | Eco-Friendly | Easy Handling and No Installation Constraints | Ready-to-Use | Long Service Life | Low Self-Discharge | Excellent Charge Retention and Recovering Ability | Superior High-Rate Discharge | High Reliability | Wide Range

APPLICATIONS: UPS System, Telecommunication Equipment, Fire Alarm & Security System, Office Automation Equipment, EPABX & Electronic Weighing Scale and in many other applications.

EP SERIES: Small and medium sized sealed lead acid battery performance characteristics conforming to JIS C8702.

SPECIFICATIONS CHART

Type of Battery	Nominal Voltage (V)	Rated Capacity (Ah) at 27 C.						Dimensions (mm)				Weight ±5% (Kg)
		20 hrs 1.75 V/cell	10 hrs 1.75 V/cell	3hrs 1.7 V/cell	1.5 hrs 1.7 V/cell	1 hrs 1.6 V/cell	30 mins. 1.6 V/cell	Overall Height (±2)	Height upto lid top (±2)	Length (±1)	Width (±1)	
EP 7-12	12	7	6.5	5.2	5.0	4.2	3.5	100	94	151	65	2.4
EP 9-12 / EP 1234 W	12	9	8.1	6.8	6.4	5.4	4.5	100	94	151	65	2.6
EP 12-12	12	12	11.2	9.0	8.6	7.2	6.0	100	94	151	98	3.8
EP 17-12	12	17	16.0	12.9	12.2	10.2	8.5	167	167	181	76	5.0
EP 26-12W (PP)	12	26	24.0	19.5	18.7	15.6	13.0	175	175	166	125	8.8
EP 26-12 (ABS)	12	26	24.0	19.5	18.7	15.6	13.0	179	179	178	124	9.2
EP 32-12 (ABS)	12	32	29.1	24.0	23.0	19.2	16.0	179	179	178	124	9.9
EP 42-12	12	42	38.5	31.5	30.2	25.2	21.0	170	170	200	165	14.0
EP 65-12	12	65	60.0	48.6	46.8	39.0	32.5	174	174	350	166	20.3
EP 75-12	12	75	69.0	56.2	54.0	45.0	37.5	174	174	391	166	23.0
EP 84-12	12	84	76.4	63.0	60.5	50.5	41.0	235	235	407	173	30.0
EP 100-12	12	100	91.0	75.0	72.0	60.0	50.0	235	235	407	173	32.5
EP 120-12	12	120	109.0	90.0	86.4	72.0	60.0	239	239	452	172	38.0
EP 150-12	12	150	136.5	112.5	108.0	90.0	75.0	240	240	557	172	48.3
EP 200-12	12	200	182.0	150.0	144.0	120.0	100.0	240	240	533	250	67.2

 Underwriters Laboratories Inc.® USA certification for the products are available as an option. FR Grade batteries are available as an option.

Statutory Notice: All batteries contain lead, which is harmful for humans and environment. As per statutory requirements, the used battery must be returned to the authorized dealer, manufacturer or at the designated collection centres.

EXIDE POWERSAFE PLUS

Contact our Exide Powercentre Showrooms for Sales & Services

Head Office

Kolkata 'Exide House', 59E Chowringhee Road, Kolkata - 700 020, Phone (033) 2283 2120/33/36/50/51/71/ 2238/39, Fax (033) 2283 2632/37

Corporate Marketing Office

Kolkata 6A Hatbagan Road, Entally, Kolkata - 700 014, Phone (033) 2286 6158/6159, Fax (033) 2286 6186, E-mail: indicare@exide.co.in

Regional Offices

New Delhi 'Exide House', 8/42 Kirtinagar Industrial Area, Opposite MDH Spice Factory, New Delhi - 110015, Phone: (011) 4144 0293/0068/ 0927/4238 1581/4237 6282/4243 3023/ 3453/ 4235 2085

Chennai Exide Industries Limited, New No. 82/42, Old No. 398, Third Floor, Anna Salai, Nandanam, Chennai - 600 035 (Before Hyundai Showroom), Phone (044) 4907 5100, (044) 4907 5125, Fax (044) 4907 5126

Mumbai 'RAHEJAS', 5th Floor, 8C Main Avenue, V P Road, Santacruz (West), Mumbai - 400 054, Phone (022) 2646 5283/84, Fax (022) 2646 5042

Kolkata 6A Hatbagan Road, Entally, Kolkata - 700 014, Phone (033) 2284 3137/3168/3169, Fax (033) 2289 7455

Branch Offices

Cuttack Ph: (0671) 234 8833

Guwahati Ph: (0361) 719 7273

Jamshedpur Ph: (0657) 229 0784/0785

Fax (0657) 229 0894 (PP)

Patna Ph: (0612) 322 3885, Fax (0612) 252 9902 (PP)

Siliguri Ph: (0353) 253 8321, Fax (0353) 252 3731

Chandigarh Ph: (0172) 500 0014

Dehradun Ph: (0135) 264 4144/324 7766

Ghaziabad Ph: (0120) 437 7031

Jaipur Ph: (0141) 519 1213/214/206,

Fax (0141) 519 1221

HUBLI Ph: (0836) 233 3404

Mangalore Ph: (0824) 428 6331

POWERSAFE PLUS is a product of ISO 9001, ISO 14001, and OHSAS 18001 certified factory

Jalandhar Ph: (0181) 500 9306/9315/9321/9322, Fax (0181) 500 9326

Lucknow Ph: (0522) 401 895/896/404 1896/1899

Varanasi Ph: (0542) 220 2129

Bengaluru Ph: (080) 4081 0807/0809, Fax (080) 2574 4226

Coimbatore Ph: (0422) 470 0105, Fax (0422) 222 0858

Hyderabad Ph: (040) 6516 3958

Kochi Ph: (0484) 414 9351, 414 9352, Fax (0484) 414 9311

Ahmedabad Ph: (079) 6510 8207, Fax (079) 2963 0532

Indore Ph: (0731) 654 2293

Mumbai (Fort) Ph: (022) 2207 2188/89, Fax (022) 2207 8631

Nagpur Ph: (0712) 253 9972/9973,

Fax (0712) 253 8348

Pune Ph: (020) 6522 2706, Fax (020) 2443 0094

Vadodara Telefax: (0265) 239 4240

This catalogue is issued to provide outline information only and is not deemed to form part of an offer or contract. Our policy is one of continued improvement and we reserve the right to change details without prior notice.

E-mail: indicare@exide.co.in, Visit us at www.exide4u.com

Toll Free No. 1800-103-5454

PHX/PS PLUS/2-2015